


SK-91ERSD (Dipole — 1,000 foot range max.)

## **FEATURES:**

- Extends range up to 1,000 feet for these SECO-LARM RF receivers:
  - SK-910RA single-channel miniature receiver,
  - SK-910R single-channel receiver,
  - SK-910R2 two-channel receiver,
  - SK-910R4 four-channel receiver.
- Easily plugs into a connector on the receiver's motherboard no extra wiring needed.
- Includes 9-foot cable.
- Power supply: +5VDC, +/- 0.1VDC (supplied by receiver's motherboard).
- Current consumption: 4.0mA.
- Sensitivity: 0.89μV @ -108dBm.
- Frequency: 315MHz.
- Bandwidth: 3.0MHz (-3dB).
- Double-stick mounting tape included.

SK-91ERSD Dipole Up to 1,000 foot range



The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

For more information, contact SECO-LARM<sup>®</sup> U.S.A., Inc. 16842 Millikan Avenue Irvine, CA 92606 Copyright© 2008 SECO-LARM U.S.A., Inc. Tel: 1-800-662-0800 (domestic U.S. & Canada) Tel: 1-949-261-2999 (California & international) Fax: 1-949-261-7326 Email: info@seco-larm.com Website: www.seco-larm.com